



PORTABLE GASOLINE GENSET

Continuous Power

The maximum power which a generating set is capable of delivering continuously whilst supplying a constant electrical load. Average load can be 100%. The generator must not be overloaded.

Standby Power

The max power available during a variable electrical power sequence, under the stated operating conditions, for which a generating set is capable of delivering in the event of a utility power outage or under test conditions for up to 200 hrs of operation per year under average of 70% load. Overloading isn't permissible.

Prime Power

The maximum power which a generating set is capable of delivering continuously whilst supplying a variable electrical load. Average load should be 70%. The generator can be overloaded 10% for 1 hour per 12 hrs.

Genset

Standby	kVA	9.5
Prime	kVA	8.6
Start System	Electric Start	
Power Factor	CosΦ	1.0
Voltage	220 or 380(50Hz)	
Fuel Type	Gasoline	
Fuel Tank Capacity	lt	30

Engine

Model	192F	
Kw (Standby/Prime)	7,5/7	
Bore / Stroke	mm	92x69
Number of Cylinder	1	
Displacement	cc	460
Oil Capacity	lt	1.1
Engine Type	4-Stroke, Air Cooled, OHV	

Size

Weight	kg	93
L x W x H	cm	70x51x55