



## PORTABLE GASOLINE GENSET

### Continuous Power

The maximum power which a generating set is capable of delivering continuously whilst supplying a constant electrical load. Average load can be 100%. The generator must not be overloaded.

### Standby Power

The max power available during a variable electrical power sequence, under the stated operating conditions, for which a generating set is capable of delivering in the event of a utility power outage or under test conditions for up to 200 hrs of operation per year under average of 70% load. Overloading isn't permissible.

### Prime Power

The maximum power which a generating set is capable of delivering continuously whilst supplying a variable electrical load. Average load should be 70%. The generator can be overloaded 10% for 1 hour per 12 hrs.

### Genset

Standby	kVA	7.5
Prime	kVA	6.8
Start System	Electric Start	
Power Factor	CosΦ	1.0
Voltage	220 or 380(50Hz)	
Fuel Type	Gasoline	
Fuel Tank Capacity	lt	30

### Engine

Model	190F	
Kw (Standby/Prime)	6,5/6	
Bore / Stroke	mm	90x66
Number of Cylinder	1	
Displacement	cc	420
Oil Capacity	lt	1.1
Engine Type	4-Stroke, Air Cooled, OHV	

### Size

Weight	kg	88
L x W x H	cm	70x51x55