



## PORTABLE GASOLINE GENSET

### Continuous Power

The maximum power which a generating set is capable of delivering continuously whilst supplying a constant electrical load. Average load can be 100%. The generator must not be overloaded.

### Standby Power

The maxpower available during a variable electrical power sequence, under the stated operating conditions, for which a generating set is capable of delivering in the event of a utilitypower outage or under test conditions for up to 200 hrs of operation per year under average of 70%load.Overloading isn't permissible.

### Prime Power

The maximum power which a generating set is capable of delivering continuously whilst supplying a variable electrical load. Average load should be 70%. The generator can be overloaded 10% for 1 hour per 12 hrs.

### Genset

Standby	kVA	11
Prime	kVA	10
Start System	Electric Start	
Alternator	NSM Saccardo	
Voltage	220 or 380(50Hz)	
Fuel Type	Gasoline	
Fuel Tank Capacity	lt	20

### Engine

Model	3564	
Hp	18	
Bore / Stroke	mm	72x70
Number of Cylinder / Type	2 / V Twin	
Displacement	cc	570
Oil Capacity	lt	1.7
Engine Type	4-Stroke, Air Cooled, OHV	

### Size

Weight	kg	145
L x W x H	cm	78x73x77