



PORTABLE GASOLINE GENSET

Continuous Power

The maximum power which a generating set is capable of delivering continuously whilst supplying a constant electrical load. Average load can be 100%. The generator must not be overloaded.

Standby Power

The maxpower available during a variable electrical power sequence, under the stated operating conditions, for which a generating set is capable of delivering in the event of a utility power outage or under test conditions for up to 200 hrs of operation per year under average of 70%load.Overloading isn't permissible.

Prime Power

The maximum power which a generating set is capable of delivering continuously whilst supplying a variable electrical load. Average load should be 70%. The generator can be overloaded 10% for 1 hour per 12 hrs.

Genset

Standby	kVA	12.5
Prime	kVA	11.3
Start System		Electric Start
Alternator		NSM Saccardo
Voltage		220 or 380(50Hz)
Fuel Type		Gasoline
Fuel Tank Capacity	lt	20

Engine

Model		3854
Hp		21
Bore / Stroke	mm	75,5x70
Number of Cylinder / Type		2 / V Twin
Displacement	cc	627
Oil Capacity	lt	1.7
Engine Type		4-Stroke, Air Cooled

Size

Weight	kg	145
L x W x H	cm	78x73x77