



PORTABLE GASOLINE GENSET

Continuous Power

The maximum power which a generating set is capable of delivering continuously whilst supplying a constant electrical load. Average load can be 100%. The generator must not be overloaded.

Standby Power

The max power available during a variable electrical power sequence, under the stated operating conditions, for which a generating set is capable of delivering in the event of a utility power outage or under test conditions for up to 200 hrs of operation per year under average of 70% load. Overloading isn't permissible.

Prime Power

The maximum power which a generating set is capable of delivering continuously whilst supplying a variable electrical load. Average load should be 70%. The generator can be overloaded 10% for 1 hour per 12 hrs.

Genset

Standby	kVA	15
Prime	kVA	13.6
Start System	Electric Start	
Alternator	NSM Saccardo	
Voltage	220 or 380(50Hz)	
Fuel Type	Gasoline	
Fuel Tank Capacity	lt	20

Engine

Model	3864	
Hp	23	
Bore / Stroke	mm	75.5x70
Number of Cylinder / Type	2 / V Twin	
Displacement	cc	627
Oil Capacity	lt	1.7
Engine Type	4-Stroke, Air Cooled	

Size

Weight	kg	160
L x W x H	cm	78x73x77